


ANKER SOLIX

Anker SOLIX F3000 Portable Power Station

3,072Wh | 3,600W

The Longest-lasting Essential Home Backup Power



Hotline: (AU) + 61 1800 929 112
Email: support@anker.com

Note: Product specifications and details are subject to change without notice.
Refer to the Anker SOLIX official website for current and accurate information.

ANKER
Innovations


| **Anker SOLIX F3000 Portable Power Station**



Rated Capacity	51.2VDC 60,000mAh / 3,072Wh
AC Input (Wall Charger)	230V~ 10A Max, 2,300W Max, 50Hz
AC Input (EV Charger)	230V~ 18A Max, 3,600W Max, 50Hz
High-PV Input	11-165V~17A Max (1,600W Max)
Low-PV Input	11-60V ~ 17A Max (800W Max)
USB-C Output	5V~3A/ 9V~3A/ 15V~3A/ 20V~3A/ 20V~5A (100W MaxPer Port)
USB-A Output	5V~ 2.4A (12W Max Per Port)
AC Output	230V~ 10A Max, 2,300W Max, Total Power 3,600W, 50Hz
AC Output (Bypass)	230V~ 9.8A Max, 2,254W Max, Total Power 2,254W, 50Hz
Car Charger Output	12V~10A
DC Output	13.4V~30A
Discharging Temperature	-20°C to 40°C
Charging Temperature	0°C to 40°C
Net Weight	41.5 kg
Dimensions (W × H × D)	651 × 300 × 377 mm
UPS Switchover Time	20 ms

| **What's in the Box**

In the F3000 Package



Anker SOLIX F3000
Portable Power Station



AC Charging Cable




High-Voltage Solar
Charging Cable




Documents

In the Expansion Battery Box (Sold Separately)



Anker SOLIX BP3000
Expansion Battery



Battery-to-Host Cable



Documents